

AAP 3500



Frekans	Hz	50
Jeneratör Modeli		AAP 3500
DY]b:]nÜh	TL	1190

x N9 @@? @F



M5? #; x GH9F; 9G
? U'Ub'nÜ_ihä]_Üfibi'b[" n'Yba Yg]b]gÜ 'ÜntÜb'XYdc
" nYf]bXY_][" ghYf[Y



C < J 'A CHCF
6U_ia 'j Y_'j 'Übia 'i'XU'U'_c'Um' ghYb'gi dUd'i'a cfcf



M5 '5@5FA =
A cfcf'nÜ_gin'_U'Xi 'ibXU', U'i 'a Ugibi'" b'YnYfY_'a cfcf
_cfi nÜb'U'Ufa 'g]ghY'a]



5J F
J c'Ü'Ü'b'&&\$'J 'j YnÜ", \$'J 'fXU'gÜV]hc'ÜfU'_U'a Ugibi
gÜ 'ÜntÜb'c'ca Uf_]j c'Ü'^fY[" 'Üf' f



5 'ifi'_Ü_ia ; Y_]X]]bXY'XYj fYm]_YgYfY_'YbYfÜh' f
_cfi nÜb' U'Yf



J C @HA 9HF 9
; fi d' nYf]bXY'5"7"u'i_]j c'Ü'Ü'ibi[" ghYfYb'_UXfÜb



> ? @9'G GH9A
'_Ü, U'i 'hifa UXUj YnÜ'gc i '_\Üj U'ÜfXU'_c'Um, U'i 'hifa U
Ua U, 'iznYb[]b'nÜ'ih'_Üfi 'ia 'i'gÜ 'ÜntÜb'g]ghY'a



u : H'9@9A 5B @=< 5J 5: @HF 9G
9a]Yb'\Üj Ubib'hc'nj Y'd]g]_YfXy'b'Üfiba Ugibi'gÜ 'ÜntÜb
,]znY'Ya Ub'i'\Üj U'Ü'ghYg]



6y My? 'M5? #H5B? =
%!)&' 'hÜfÜgi'nÜ'ih'Üb'_i

AAP 3500

JENERATÖR

AC Nominal Güç	kW	2,50
	kVA	3,00
Maksimum Güç	kW	2,80
	kVA	3,50
57 'Bca]bU'5_ia	57 'Bca]bU'5_ia	10,00
Voltaj	V	230
Frekans	Hz	50
: Un'GUmgj		1
Güç Faktörü		0,80
MU_ihH' _Yfja]	L/sa	1,10
Gürültü Seviyesi	dB(A)	76,00

MOTOR

Devir	d/dk	3000
Güç	Hp	6,5
Silindir No.		1,0
Silindir Hacimi	mL.	196
MU_ihH' f'		Benzin
MU_?UdUg]HYg]	L	0,6
MU_ihHUb_?UdUg]HYg]	L	15,0
GRUfh Y_]		d']

BOYUT

En	mm.	605
Boy	mm.	490
Yükseklik	mm.	490
5 ifi_	kg.	50,0